

# DLW5BSM302SQ2#

Note: This datasheet may be out of date.

Please download the latest datasheet of DLW5BSM302SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=DLW5BSM302SQ2%23

"#" indicates a package specification code.








< List of part numbers with package codes > DLW5BSM302SQ2B DLW5BSM302SQ2K

DLW5BSM302SQ2L



### Appearance & Shape







## Packaging Information

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	100
К	330mm Embossed Tape	1500
L	180mm Embossed Tape	400



# **Applications**

Other Usage

For general

1 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





# DLW5BSM302SQ2#

Note: This datasheet may be out of date.

Please download the latest datasheet of DLW5BSM302SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=DLW5BSM302SQ2%23

"#" indicates a package specification code.



### **Features**

DLW5AH/5BS series is a high performance wound type chip common mode choke coil.

#### Features

- 1. High impedance (max. of 4000ohm at 100MHz: DLW5AH) enables great noise suppression.
- 2. Large rated current (max. of 5A) is suitable for power line use.
- DLW5AH/BS series does not damage high speed signal due to high coupling common mode choke coil structure.
- 4. Automatic mounting can be applied.

### **Applications**

- 1. DC power lines in AC adapters of Portable equipment
- 2. DC power lines of DC-DC converters, battery chargers

2 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# DLW5BSM302SQ2#

Note: This datasheet may be out of date.

Please download the latest datasheet of DLW5BSM302SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=DLW5BSM302SQ2%23

"#" indicates a package specification code.



# **Specifications**

Shape	SMD
Size Code (in mm)	5050
Size Code (in inch)	2020
Length	5.0mm
Length Tolerance	±0.3mm
Width	5.0mm
Width Tolerance	±0.3mm
Thickness	4.5mm
Thickness Tolerance	max.
Common Mode Impedance (at 100MHz)	3000Ω
Common Mode Impedance (at 100MHz) Tolerance	(Тур.)
Common Mode Impedance (at 10MHz)	300Ω
Common Mode Impedance (at 10MHz) Tolerance	min.
Rated Current	500mA
Derating of Rated Current	No
Rated Voltage	50Vdc
Withstanding Voltage	125Vdc
DC Resistance(max.)	0.3Ω
DC Resistance	0.3Ω max.
Insulation Resistance(min.)	10ΜΩ
Operating Temperature Range	-40°C to 85°C
Mass(typ.)	0.3g
Number of Circuit	1

Operating Temperature		
Range(Self-temperature rise	No	
is included)		

3 of 4

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

<sup>2.</sup> This datasheet has only typical specifications because there is no space for detailed specifications.

### NNOVATOR IN ELECTRONICS

DLW5BSM302SQ2#


Note: This datasheet may be out of date.


Please download the latest datasheet of DLW5BSM302SQ2# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en-us/products/productdetail?partno=DLW5BSM302SQ2%23

"#" indicates a package specification code.








Impedance-Frequency Characteristics

Impedance-Frequency Characteristics (Main Items)



**Equivalent Circuit** 

4 of 4

### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications.
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Murata:

DLW5BSM302SQ2L