

Note: This datasheet may be out of date. Please download the latest datasheet of BLM21PG121SZ1# from the official website of Murata Manufacturing Co., Ltd. ata.com/en-GB/products/productdetail?partno=BLM21PG121SZ1%23

BLM21PG121SZ1#

"#" indicates a package specification code.



< List of part numbers with package codes > BLM21PG121SZ1D BLM21PG121SZ1J BLM21PG121SZ1B





0.85±0.2

(in mm)

Packaging Information

\square		
	40	



Packaging	Specifications	Minimum Order Quantity
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000
В	Bulk(Bag)	1000

Applications

Automotive Usage

Infotainment

1 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Attention



Note: This datasheet may be out of date. Please download the latest datasheet of BLM21PG121SZ1# from the official website of Murata Manufacturing Co., Ltd. om/en-GB/products/productdetail?partno=BLM21PG121SZ1%23

BLM21PG121SZ1#

"#" indicates a package specification code.



- 1. The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.
- 2. The nickel barrier structure of the external
- electrodes provides excellent solder heat resistance.
- 3.BLM_P series can be used in high current circuits due to its low DC resistance. It can match power lines to a maximum of 6ADC.

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

2 of 4



Note: This datasheet may be out of date. Please download the latest datasheet of BLM21PG121SZ1# from the official website of Murata Manufacturing Co., Ltd. http://www.murata.com/en-GB/products/productdetail?partno=BLM21PG121SZ1%23

BLM21PG121SZ1#

"#" indicates a package specification code.

Specifications

Shape	SMD
Size Code (in mm)	2012
Size Code (in inch)	0805
Length	2.0mm
Length Tolerance	±0.2mm
Width	1.25mm
Width Tolerance	±0.2mm
Thickness	0.85mm
Thickness Tolerance	±0.2mm
Impedance (at 100MHz)	120Ω
Impedance (at 100MHz) Tolerance	±25%
Rated Current (at 85°C)	3A
Rated Current (at 125°C)	1.55A
DC Resistance(max.)	0.03Ω
Operating Temperature Range	-55°⊂ to 125°⊂
Mass(typ.)	0.01g
Number of Circuit	1

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Attention



Note: This datasheet may be out of date. Please download the latest datasheet of BLM21PG121SZ1# from the official website of Murata Manufacturing Co., Ltd. m/en-GB/products/productdetail?partno=BLM21PG121SZ1%23

BLM21PG121SZ1#

"#" indicates a package specification code.

Product Data



Impedance-Frequency Characteristics

In operating temperature exceeding +85°C, derating of current is necessary for BLM21PG series. Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current







Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Murata: BLM21PG121SZ1D